

SPEKTRUM DX7 ELECTRIC AIRPLANE KILL SWITCH

- Turn transmitter on.
- Press the down and select keys simultaneously to access FUNCTION MODE.
- In FUNCTION MODE use up or down keys to select the desired PROGRAM MIX screen (1 thru 6).
- Next press INCREASE or DECREASE keys to change the values shown in picture shown below.

(ref.) page 58 in instruction book.

INFO. PROVIDED BY “HORIZON HOBBIES”



Verbal Description (by John McCormick)

- Pick one of the PROG. Mix 3 through 6.
- Make sure both the Master and Slave channels are THRO.
- Highlight and set the Offset to -200.
- Pick your kill switch (suggest either GER or MIX). Leave THRO STIK in INH.
- Both Pos0 values should be 0%. Highlight Pos1.
- The top position should be highlighted and at 0%.
- As you move the throttle stick, the highlighted position should not change.
- Set the top position to -100%. Leave the bottom value for Pos1 at 0%.

I use this method for my electrics. The throttle trim does not affect the kill position.